

# MAGMATIC JAVELIN - DMX TRAITS

CHANNEL				VALUES	FUNCTION
1-CH	4-CH	7-CH	12-CH		
1					<b>Fog</b>
				000 - 009	Off
				010 - 127	LED on (switches LEDs on w/ 1-second delay)
				128 - 255	Max Fog with LED On
	1	1	1		<b>Fog</b>
				000-031	Off
				032-255	Max Fog
	2				<b>Macro</b>
				000 - 004	LED Off
				005 - 154	Macros 1 - 75 (see Macro Table)
				155 - 180	Fog burst & lighting display loop (2s loop)
				181 - 205	Fog burst & lighting display loop (1s loop)
				206 - 230	Auto 2
				231 - 255	Auto 1
		2	2	000-255	<b>Red1, 0 to 100%</b>
		3	3	000-255	<b>Blue1, 0 to 100%</b>
		4	4	000-255	<b>Amber1, 0 to 100%</b>
		5	5	000-255	<b>Red2, 0 to 100%</b>
		6	6	000-255	<b>Green2, 0 to 100%</b>
		7	7	000-255	<b>Blue2, 0 to 100%</b>
		8	8	000-255	<b>Amber2, 0 to 100%</b>
		9	9	000-255	<b>Red3, 0 to 100%</b>
		10	10	000-255	<b>Green3, to 100%</b>
	3	11	11		<b>Strobe</b>
				000 - 031	Off
				032 - 095	Random, slow to fast
				096 - 159	Pulse Effect, in sequence
				160 - 255	Strobe, slow to fast
	4		12		<b>Dimmer</b>
				000 - 003	LED Off
				004 - 255	1% to 100%