

MAGMATIC JAVELIN - DMX CHANNEL FUNCTIONS & VALUES

CHANNEL				VALUES	FUNCTION
1-CH	4-CH	7-CH	12-CH		
1	1	1	1		Fog
				000 - 009	Off
				010 - 127	LED on (<i>switches LEDs on w/ 1-second delay</i>)
				128 - 255	Max Fog with LED On
	2				Macro
				000 - 004	LED Off
				005 - 154	Macros 1 - 75
				155 - 180	Fog burst & lighting display loop (2s loop)
				181 - 205	Fog burst & lighting display loop (1s loop)
				206 - 230	Auto 2
				231 - 255	Auto 1
		2	2	000 - 255	Red1, 0 to 100%
		4	3	000 - 255	Blue1, 0 to 100%
		5	4	000 - 255	Amber1, 0 to 100%
			5	000 - 255	Red2, 0 to 100%
		3	6	000 - 255	Green2, 0 to 100%
			7	000 - 255	Blue2, 0 to 100%
			8	000 - 255	Amber2, 0 to 100%
			9	000 - 255	Red3, 0 to 100%
			10	000 - 255	Green3, 0 to 100%
	3	6	11		Strobe
				000 - 031	Off
				032 - 095	Random, slow to fast
				096 - 159	Pulse Effect, in sequence
				160 - 255	Strobe, slow to fast
	4	7	12		Dimmer
				000 - 003	LED Off
				004 - 255	1% to 100%