



SDC12™

sku# SDC12

The new SDC12™ features 12 DMX channels, DIP switches to set a starting DMX channel, a master dimmer fader, on/off switch, 3pin and 5pin XLR output, and operates via an external 12VDC power supply (included) or a 9VDC battery (not included).

Great handheld device for product demos or manual control of LED or conventional fixtures. Can be wall mounted for permanent installations.

FEATURES

- 12 DMX Channels Faders
- Master Dimmer Fader
- Portable Handheld Or Wall Mountable
- Operates via External 12VDC Power Supply (Included) Or 9VDC Battery (Not Included)

CONTROL / CONNECTIONS

- DIP Switches To Set Starting DMX Channel
- 3pin & 5pin DMX Outputs
- On/Off Switch
- LED Channel Bank Indicator
- DC 12V Power Supply Input

SIZE / WEIGHT

- Length: 7.5" (191mm)
- Width: 5.9" (149mm)
- Height: 1.6" (41mm)
- Weight: 2.0 lbs. (0.9kg)



Specifications subject to change without notice ©Elation Professional

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands
+31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu